



The newest generation of the 315w CMH ballast was developed to optimize the output of our 315w CMH lamps. Our lamp and ballast are tuned to work together at over 99% efficiency when operated together, you will receive less color shifts, lower lamp temperatures, and less frequency humming.

#### Features

- CMH lamps
- Soft Start stabilizes start-up loads and extends lamp life & performance
- Low frequency (<200 Hz), Constant output
- LED status display
- 6' 120VAC power cord provided
- 120/208/240/277VAC voltage sensing input
- 3 year warranty
- UL listed for safety

#### Protections

- Short circuit
- Open circuit
- End of Lamp Life (EOL)
- Hot-Start
- Ignition Failure
- Overheat
- Over/Under voltage

#### Performance

- Rated Voltage: AC90-305VAC
- Input Frequency: 50/60Hz
- Ambient Operating Temperature (TA): -25°C ~ 50°C (-13°F ~ 122°F)
- Crest Factor (CF): <1.5
- Power Factor (PF): ≥0.95
- Max case temperature <80°C (<176°F)
- Total Harmonic Distortion (THD): <20%
- Current Draw: 2.84A @ 120VAC, 1.42A @ 240V, 1.23A @ 277VAC
- Dimensions: L 8.75" x W 5.07" x H 3.125"

Weight: 5.5 lbs/2.5kg

Item No.: GLB-315-A-120/277

